



SECURE-TECH
DETENTION ELECTRONIC SYSTEMS
 ETECH CONTROLS CORPORATION - MANUFACTURER
 4051 ALVIS COURT #3, ROCKLIN, CALIFORNIA, USA 95677
 TEL (916) 630-1300 • FAX (916) 630-1100 • FREE (800) 800-2523

**MODEL-
 #PAT**

303.875MHz DURESS TRANSMITTER REPLACEMENTS

Secure-Tech.com introduces direct 303.875MHz DURESS TRANSMITTER REPLACEMENTS, for all CDCR PERSONAL ALARM SYSTEMS.

Etech introduces two (2) new lines of Secure-Tech.com 303.875MHz RF-Duress Transmitters, for use with all existing CDCR LINEAR based Personal Duress Systems. These replacement CDCR Duress-Transmitters have been developed and tested to directly replace the discontinued LINEAR brand Model #D22-A Transmitter unit. Both replacement Secure-Tech.com Transmitter models undergo full, individual factory RF calibration and range testing to guarantee their performance and compatibility with all existing CDCR installed, LINEAR model #D-67 RF Receivers.

NEW!
 Secure-Tech.com
**PERSONAL
 ALARM
 TRANSMITTERS
 (#PAT):**



Manufacturer:	Linear (discontinued)	Etech	Etech
Model #:	#D-22A (original)	#PAT-D22A-L	#PAT-D22A-S
General:	Original Linear Model #D-22A. Discontinued 2019.	Exact Size and Dimensions of original LINEAR #D-22A. Perfect fit in all existing CDCR Duress "Holsters".	Fits all existing CDCR Duress Holsters. Superior RF "Crystal-Locked" Transmit quality and stability.
Frequency:	303.875MHz	303.875MHz	303.875MHz
Tuning Circuit Type:	Crystal Locked, for superior frequency stability.	Tuned LC Circuit.	Crystal Locked, for superior frequency stability.
Programmability:	256 Switch Selectable Codes	256 Switch Selectable Codes	256 Switch Selectable Codes
Code Selection:	8-position Dip-Switch	8-position Dip-Switch	8-position Dip-Switch
Transmitter Format:	LINEAR D-22A Protocol	LINEAR D-22A Protocol	LINEAR D-22A Protocol
Features:	Single Push Button. Transmit Red LED. Optional Belt Clip	Single Push Button. Transmit Red LED. Optional Belt Clip.	Single Push Button. Transmit Red LED. Optional Belt Clip.
Battery Type:	9v – Standard Battery	9v – Standard Battery. Special battery NOT required.	3v – #CR2032 Coin Battery.
Warranty:	2-Year Warranty	2-Year Warranty	2-Year Warranty
Operation:	Single Button on face. Aligned to existing Duress Holsters.	Single Button on face. Aligned to existing Duress Holsters.	Single Button on face. Aligned to existing Duress Holsters.
Compatibility:	Compatible with all existing CDCR #D-67 LINEAR Duress receivers, as well as the Secure-tech.com #PAR-D67 series fully "Power-Supervised" Duress Receivers.	Compatible with all existing CDCR #D-67 LINEAR Duress receivers, as well as the Secure-tech.com #PAR-D67 series fully "Power-Supervised" Duress Receivers.	Compatible with all existing CDCR #D-67 LINEAR Duress receivers, as well as the Secure-tech.com #PAR-D67 series fully "Power-Supervised" Duress Receivers.
Dimensions:	3.75"H x 2.16"W x .95"D	3.75"H x 2.16"W x .95"D (exact size direct replacement to original #D-22A)	3.5"H x 2.25"W x .75"D. Closely fits all CDCR Duress Holsters.

*Note: All RF-Transmitter units shown directly replace the original LINEAR Model #D22A, 303.875MHz Transmitter, including all of the LINEAR #D-22A's original features, functions and full physical RF-transmitter range.